



Multi Sound Siren WSR102

Smart Home Multi-Sensor is well designed for detection of various home environment changing, like: open and close of doors and windows, human and animal motion, illumination and temperature changing. Besides the detection function, it triggers the Control Center to send out warning messages.

Features

- ▶ Z-Wave 500 series module inside
- ▶ Higher output power to enhance the communication range (+5dBm output power as compared to -2.5dBm 300 series)
- ▶ Build-In Six Different Sounds
- ▶ 110 dB Sounds
- ▶ With tamperproof protection
- ▶ Elegance white appearance
- ▶ Invisible antenna design
- ▶ Easily Hang Up On Wall
- ▶ EN 300 220, EN 301 489
- ▶ EN 55022
- ▶ EN 61000 ,EN 60950
- ▶ FCC Part 15 B

Specification

Hardware

Supply Voltage	5.0 V Power Adapter
Standby Current	40 mA
Operating Current	150 mA
Alarm Sound	110 dB
Low Battery	3.5 V
Voltage	
Battery Shutdown	3.4 V
Voltage	
Battery Lifetime	24 Hours
Z-Wave	Z-wave 500 Series Module
RF Frequency	868.4MHz, 869.85MHz (EU) 908.4MHz,916.0MHz(USA) 922~927MHz (Taiwan/JP) Frequency for other country/area is also available for order.
RF Range	Z-Wave: 100M in open space

Sounds

Six Sounds	(1). Door Chime (2). Beep (3). Intruder Alarm (4). Fire Alarm (5). Ambulance (6). Police Car
------------	--

Mechanical

Dimensions	110L x110W x19H mm
Weight	115g

Environment

Operating Temp.	-10°C ~ 40°C
Humidity	85% RH max