



## IR Network Vandal Dome Camera

**CAM415 / CAM415-PoE**

- ▶ Vandal-proof Network Dome Camera
- ▶ MPEG4 / MJPEG Dual mode & Dual streaming
- ▶ IR distance up to 12 meters
- ▶ Support SD card for local record
- ▶ 2-way audio
- ▶ 3GPP for monitoring via 3G mobile phone
- ▶ IP-66 waterproof standard
- ▶ Optional embedded PoE (CAM415-PoE)
- ▶ Free 36CH recording software

**Specification****Hardware**

CPU	ARM 9, 32 bit RISC
RAM	64MB
ROM	8MB
Image Sensor	1/3" Sony SuperHad CCD, 520 TV lines
Lens	Vari-focal 3.7 ~ 12 mm, F1.6
IR Distance	12 Meters
Sensitivity	Normal: 0.1 lux, IR On: 0 lux
Video Out	1 Analog video out (BNC connector)
Audio In/ Out	1 Line in / 1 Line out (RCA connectors)
Digital I/O	1 In / 1 Out
Water Proof	IP-66 standard
Power Supply	CAM415: DC 12V, 1A CAM415-PoE: Embedded PoE Splitter (IEEE 802.3af)
Dimensions	Φ138 x H105 mm

**Network**

Ethernet	10/ 100 Base-T
Network Protocol	HTTP, TCP/IP, RTP/RTSP, 3GPP, NTP, SMTP, FTP, PPPoE, DHCP, DDNS, UPnP

**Event System**

Event Trigger	Motion Detection, Sensor In
Trigger Actions	Send Email, Send to FTP, Save to SD Card, Digital Out

**Client Requirements**

OS	Windows 2000, XP, 2003, IE6.0
Suggested	Intel-C 2.0G, RAM: 512MB, Graphic card: 64MB

**System**

Video Resolution	NTSC: 720x480, 704x480, 352x240, 176x120 PAL: 720x576, 704x576, 352x288, 176x144
Compression Format	MPEG-4 / MJPEG
Frame Rate	Up to 30 FPS
Video Bitrate Adjust	CBR, VBR
Dual Streaming	Yes
3GPP	Yes, Live view with 3G mobile phone
Image Snapshot	Yes
Video Adjust	Brightness, Contrast, Saturation, Hue, BLC
Motion Detection	Yes, 3 different areas
Pre/ Post Alarm	Yes, configurable
Security	Password protection
Connection	Up to 10 clients simultaneously
Firmware Upgrade	HTTP mode, remotely
Audio	Yes, 2-way

**SD Card Management**

Recording Trigger	Motion Detection, Sensor In, IP Check, Network Disconnect
Video Format	AVI, JPEG
Video Playback	Yes
Delete Files	Yes

**Package List**

Camera, Power Adapter (not included with PoE model), Ethernet Cable, Screws&Tool, CD-ROM, Quick Installation Guide